

**TABLA 2. EFICIENCIA NOMINAL PARA MOTORES ELÉCTRICOS MONOFÁSICOS DE INDUCCIÓN  
TIPO JAULA DE ARDILLA**

Potencia		Tensión eléctrica nominal								
kW		115 V			127 V			200 - 240 V		
Mayor o igual a	Menor que	Número de polos								
		2	4	6	2	4	6	2	4	6
		Eficiencia nominal en %								
0,005	0,008	40,0	38,0	36,0	40,0	38,0	36,0	39,0	37,5	36,0
0,008	0,014	42,0	40,0	38,0	40,0	38,5	37,0	39,0	37,5	36,0
0,014	0,023	44,5	42,5	40,5	43,5	41,5	39,0	41,5	39,5	37,5
0,023	0,041	47,0	45,0	43,0	46,0	44,0	42,0	44,0	42,0	40,0
0,041	0,077	49,5	47,0	44,5	47,5	45,5	43,5	45,5	43,5	41,5
0,077	0,142	52,0	49,5	47,0	50,0	48,0	46,0	48,0	46,0	44,0
0,142	0,187	54,5	52,0	50,0	52,0	50,0	48,0	50,0	48,0	46,0